

Received June 1, 2016, accepted June 16, 2016, date of publication June 21, 2016, date of current version July 7, 2016.

Digital Object Identifier 10.1109/ACCESS.2016.2582786

4G/5G Multiple Antennas for Future Multi-Mode Smartphone Applications

YONG-LING BAN¹, CHUAN LI¹, CHOW-YEN-DESMOND SIM², (Senior Member, IEEE),
GANG WU³, (Member, IEEE), AND KIN-LU WONG⁴, (Fellow, IEEE)

¹School of Electronic Engineering, University of Electronic Science and Technology of China, Chengdu 611731, China

²Department of Electrical Engineering, Feng Chia University, Taichung 407, Taiwan

³National Key Laboratory of Science and Technology on Communication, University of Electronic Science and Technology of China, Chengdu 611731, China

⁴Department of Electrical Engineering, National Sun Yat-sen University, Kaohsiung 80424, Taiwan

Corresponding author: Y.-L. Ban (byl@uestc.edu.cn)

This work was supported in part by the National Natural Science Foundation of China under Grant 61471098, in part by the Mainland-Hong Kong-Macau-Taiwan Science and Technology Cooperation Project under Grant 2015DFT10170, and in part by the Taiwan Institute of Economic Research Cross-Strait 5G Project under Grant FY105.

ABSTRACT A hybrid antenna is proposed for future 4G/5G multiple input multiple output (MIMO) applications. The proposed antenna is composed of two antenna modules, namely, 4G antenna module and 5G antenna module. The 4G antenna module is a two-antenna array capable of covering the GSM850/900/1800/1900, UMTS2100, and LTE2300/2500 operating bands, while the 5G antenna module is an eight-antenna array operating in the 3.5-GHz band capable of covering the C-band (3400–3600 MHz), which could meet the demand of future 5G application. Compared with ideal uncorrelated antennas in an 8×8 MIMO system, the 5G antenna module has shown good ergodic channel capacity of ~ 40 b/s/Hz, which is only 6 b/s/Hz lower than ideal case. This multi-mode hybrid antenna is fabricated, and typically, experimental results such as S-parameter, antenna efficiency, radiation pattern, and envelope correlation coefficient are presented.

INDEX TERMS MIMO, multi-antenna, multi-mode, channel capacity, 5G application.

I. INTRODUCTION

With the rapid development of radio access technologies, wireless communication network environment has become a mixture of different kinds of heterogeneous networks. As a result, the development and exploitation of multi-mode mobile terminals has aroused worldwide interest in the wireless communication field [1]. Thus, multi-mode and multi-band smart phone antenna is a prerequisite requirement for present and future terminal devices, especially those with MIMO (multiple-input-multiple-output) system included. Due to the limited volume size of mobile terminal devices (such as mobile handset), strong mutual coupling among antenna elements is inevitable, which results in affecting the antenna efficiency and also influences the correlation. Therefore, it is vital to apply decoupling technique between antenna elements for MIMO system.

A number of techniques have been reported to mitigate strong mutual coupling between two antenna array elements for MIMO system [2]–[8]. Amid these techniques, besides loading a slit into the ground [2], other conventional methods such as protruding a single or dual ground

branch have also been proposed to acquire low mutual coupling [3]–[5]. Recently, novel neutralization technique has also been reported, in which a neutralization line (NL) is linked between the feeding strips or the shorting strips of antenna elements [6]–[8]. By doing so, reverse coupling can be excited to reduce the mutual coupling between antenna elements that are within very close proximity. Thus, in this paper, a previously reported antenna design [9] for 4G applications (4G antenna module) is initially reinvestigated and slightly modified. Here, a combination of protruded ground and NL techniques are applied into this antenna, so that enhanced isolation can be achieved for this 4G antenna module.

Because of the demand for faster data transmission well beyond the 4G standard, some countries and regions have already defined their very own fifth generation (5G) wireless standards that will be 100 times faster than the fastest 4G LTE standard currently available [10]. In November 2015, one of the key outcomes of WRC-15 (World Radio Communication Conference 2015) is the allocation of 3.5-GHz C band (3400–3600 MHz) as future broadband mobile services [11]. Therefore, besides considering the possibility of

implementing beamforming techniques which are envisaged as enablers for 5G mobile systems, mobile terminal device with massive MIMO antenna array operating in this C band is presently also a good candidate for future 5G operation.

To the best of author’s knowledge, most internal mobile phone with dual element MIMO antenna array designs usually cover the LTE/WWAN operation [9], [12], which only takes into the consideration of 4G frequency bands. On the other hand, the work reported in [13] has proposed a hybrid dual-antenna formed by an inverted-F antenna and an open-slot antenna that only focus on 3.6-GHz band (3.4–3.8 GHz) operation [13]. To satisfy future 5G applications, MIMO antennas for 5G applications have been discussed in [14] and [15]. For smartphone applications, the recent works reported in [16]–[18] have proposed 8-element 10-element and 16-element antenna arrays, respectively, for massive MIMO operation in the 3400–3600 MHz frequency band, however, they have failed to satisfy either multi-mode or multi-antenna design need for 4G frequency bands. Notably, other investigations have also been performed for 4G systems in the 3.4–3.6 GHz frequency band, although they are initially studied for WiMAX system [19], [20].

In this paper, a hybrid antenna composed of two modules (4G antenna module and 5G antenna module) is proposed, the novelty of this paper is the use of 8×8 MIMO array instead of a single antenna. The 4G antenna module is a two-antenna array (2×2 MIMO configuration) that can cover the GSM850/900/1800/1900, UMTS2100, and LTE2300/2500 operating bands. As for the 5G antenna module, it consists of eight identical antenna elements (8×8 MIMO configuration) operating in the 3.5-GHz band (3.4–3.6 GHz) for future 5G communication. Typical results such as S-parameters and radiation performances of this proposed antenna are presented in this study, and as predicted, the 5G antenna module can significantly improve the ergodic channel capacity as compared with a SISO (single input single output) type.

II. PROPOSED ANTENNA DESIGN

Fig. 1(a) shows the complete geometry of proposed multi-antenna module. As illustrated in Fig. 1(a), a 0.8-mm thick FR4 substrate that has a relative permittivity of 4.4 and a loss tangent of 0.024 is used as the system circuit board. The whole system circuit board has a dimension of $140 \text{ mm} \times 70 \text{ mm}$, in which a $130 \text{ mm} \times 70 \text{ mm}$ ground plane is printed onto it to serve as the system ground plane. Here, a $9.5 \text{ mm} \times 12 \text{ mm}$ protruded ground plane is connected to the system ground for decoupling and impedance matching [9]. The two 4G antennas (Ant1 and Ant2) are placed at the bottom edge of the system ground plane, separated by a protruded ground, while the eight 5G antennas are printed along two long side edges.

A. 4G ANTENNA MODULE

The 4G antenna module design proposed here is an extended version of the antenna array reported in [9] that can cover WWAN/LTE operation bands. It is composed of




FIGURE 1. (a) Configuration of proposed antenna, (b) Structure of 4G and 5G antenna modules.

two 4G antennas, and its detailed structure and optimized dimensions are given in Fig. 1(b). Each 4G antenna is comprised of a feeding strip fed by a 50Ω mini coaxial feeding line (with point A1 and A2 serving as the feeding point) and a bended shunting strip embedded with a 6.8 nH chip inductor (with point B1 and B2 serving as shunting point). As discussed earlier, the protruded ground plane is to provide decoupling effects in the upper bands and improving the impedance matching in the lower bands, however, it will also lead to deterioration of isolation in the lower bands. Thus, a neutralization line (NL) is loaded between the two 4G antenna elements, so that the decoupling effects in the lower bands can be improved. Notably, the results of this 4G antenna module are similar to the one reported in [9]. The feeding strip and shunting strip can excite a fundamental resonant mode at 950 MHz and 850 MHz, respectively, forming a combined dual resonance that can cover the lower bands for GSM850/900 operations. In addition, the shunting strip can also generate a higher-order resonance at 1800 MHz, which combined with the resonance at about 2600 MHz (introduced by the protruded ground) can cover the GSM1800/1900/UMTS operations.




FIGURE 2. Simulated S-parameters of Ref1 and proposed 4G antenna module.

As previously mentioned, the NL loaded between the two 4G antenna elements is for increasing the isolation in the lower bands. To analyze the function of this NL, Fig. 2 shows the simulated S-parameters of the proposed 4G antenna array, and a reference antenna 1 (Ref1) that is the proposed one without the NL. By loading the NL into Ref1, the proposed one has shown an enhancement in isolation (S21) of at least 3 dB in the lower bands, especially at 900 MHz, in which the S21 is improved from -7.5 dB to -11.25 dB. Therefore, the proposed 4G antenna module can successfully cover the GSM850/900/1800/1900/ UMTS/LTE2300/2500 bands with desirable isolation.




FIGURE 3. Simulated surface current distributions of Ref1 (left) and proposed 4G antenna module (right) at 950MHz.

To further validate the results of Fig. 2, Fig. 3 shows the current distributions of Ref1 and proposed 4G antenna array at 950 MHz. In both cases, their respective Ant1 is excited and Ant2 is terminated to 50Ω load. Compared with Ref1, the surface current distribution along Ant2 of proposed one is visibly reduced (lower mutual coupling). This is because the NL has modified the current distributions on the system ground plane of Ant2, with intense current on the NL that leads to corresponding strong phase-reversal coupling, which could offset the original mutual coupling [21].

B. 5G ANTENNA MODULE

Figure 1 shows the configuration of the proposed 5G antenna module, and its detail dimensions are also presented. The proposed 5G antenna module is formed by eight identical antennas (Ant3 to Ant10) printed along the two long side

edges of the system circuit board. Eight rectangular clearance regions of $16\text{ mm} \times 3\text{ mm}$ are also reserved for accommodating the proposed 5G antennas. The adjacent two antennas located on the same side edge has a spacing of 17 mm, and all the 5G antennas are arranged to have their open-end pointing toward the same direction (positive y-axis). Here, Ant3 and Ant7 are 10 mm away from the 4G antenna module, while Ant6 and Ant10 are 5mm away from the top ground edge. Each antenna element of the proposed 5G array is a bending monopole strip printed along the perimeter (about 35 mm in total length and 0.5 mm in width) of the clearance region located below it. All 5G antennas are excited through a 50Ω SMA connector. As depicted in Fig. 1(b), a protruded tuning stub (AB) of only 0.7 mm is extended from the open end of the 5G monopole strip. Besides the ability to enhance the capacitive coupling between the tuning stub and the ground plane, simply extending the length of this tuning stub can shift the excited monopole resonant mode to the lower frequency band. Here, the dimension of this 5G monopole is specifically designed for covering the 3.5 GHz band (3400–3600 MHz) [11].




FIGURE 4. Simulated S-parameters of 5G antennas.

Figure 4 shows the simulated reflection coefficients of Ant3–Ant6, and their corresponding isolations (S43, S54 and S65). All 5G antenna elements located on the right side edge have shown good impedance matching of less than 10 dB between 3400–3600 MHz. Due to enough distance among each elements, good isolation of less than 10 dB are also exhibited between any two antennas. For brevity, those on the left side edge (Ant7–Ant10) will not be presented. It is noteworthy that Ant6 has a shorter distance of 5 mm to the top ground edge, as compared with that of Ant3, Ant4, Ant5 that have longer distances to the top ground edge. From Ant3 to Ant6, the distance from the open-end of these monopoles to the top ground edge decrease gradually, which leads to a gradual degradation in the impedance matching from Ant3 to Ant6. It is also observed that the degradation of the impedance matching makes the antenna efficiency decrease gradually (Ant3–Ant6) in the 3.5 GHz band, which can be seen in Fig. 5. Here, the antenna efficiency for Ant1 is approximately 65%–70%, while that of Ant4, Ant5, Ant6 are approximately 56%–63%. As a result, the efficiencies of




FIGURE 5. Simulated efficiencies of 5G antennas along the right side edge.




FIGURE 7. Simulated input impedances of 5G antenna element.

these 5G antennas can still meet the requirement for smart-phone applications.

To fully comprehend the excitation of the 5G monopole resonant mode, the simulated surface current distributions at 3.5 GHz of Ant3 (representing the rest) is shown in Fig. 6. In this figure, a current null is observed along monopole strip with total length of 35 mm (approximately $0.41\lambda_0$), which indicates that the 3.5 GHz mode is a higher-order resonance. To explain this phenomenon, Fig. 7 shows the fundamental resonance (with reactance value is zero) of the 5G monopole is actually at approximately 1.75 GHz. However, this fundamental resonance has exhibited very poor impedance matching due to very small resistance value. Thus, it has very little influence on the 4G antenna module operating bands.




FIGURE 6. Simulated surface current distribution at 3.5 GHz for Ant3.

III. RESULT AND DISCUSSION

A. S-PARAMETERS AND ANTENNA EFFICIENCY

The proposed multi-antenna array prototype was fabricated and tested, and its front and back photographs are shown in Fig. 8. The simulated results were performed by using Ansoft HFSS ver. 14, and an Agilent N5247A vector network analyzer was used for the measured S-parameters results. Due to identical dimensions and symmetrical placement of the ten array elements, only S-parameters of Ant1 and Ant2 (4G antenna module), and Ant3–Ant6 (5G antenna module) are presented.

The measured and simulated return losses of the prototype 4G and 5G antenna modules are presented in Fig. 9(a) and (b), respectively. In this figure, good agreement




FIGURE 8. Photograph of the fabricated multi-antenna array prototype.

between the simulation and measurement are obtained. Slight differences or variations between the two results may be due to imperfect SMA connector assembly, fabrication tolerance and inevitable small misalignment between the 5G monopole strip and its bottom clearance zone.

As shown in Fig. 9(a), the 4G antennas have exhibited desirable measured 6-dB impedance bandwidths (3:1 VSWR) of 16% (823–968 MHz) and 46% (1697–2706 MHz), and measured isolation better than 10-dB in both desired frequency bands. As for the 5G antennas (Ant3–Ant6) shown in Fig. 9(b), Ant6 has shown a minimum measured 6-dB impedance bandwidth (3:1 VSWR) of approximately 12% (3300–3720 MHz), while Ant3–Ant5 have shown even better impedance bandwidths that can also cover the 3.5 GHz operating band. Because the isolations of nonadjacent 5G elements are much larger than 18 dB, for brevity, Fig. 9(b) only just shows the isolation between adjacent antenna elements (Ant3–Ant6), and the measured results (S43, S54, and S65) across the 3.5 GHz band were better than 10-dB.




FIGURE 9. S-parameters of (a) 4G antenna module, (b) 5G antenna module.




FIGURE 10. Measured antenna gains and radiation efficiencies across the operating bands of proposed multi-antenna module.

The antenna efficiencies (includes mismatching losses) and antenna gains of proposed multi-antenna module were measured with one antenna excited while the other antennas terminated to 50Ω matched load in the SATIMO microwave anechoic chamber, and the results are shown in Fig. 10. In this figure, the measured 4G antenna (Ant2) efficiencies over the lower and upper bands were more than 40% and 60%, respectively, while their corresponding antenna gain variation were -0.5 – 0.43 dBi and 0.99 – 3.7 dBi. Within the desired 3.5 GHz bands (3400–3600 MHz), the measured 5G antennas (Ant3–Ant6) efficiencies were about 62%–78%, while its corresponding antenna gains were approximately 1.9–3.2 dBi.




FIGURE 11. Calculated ECC from the measured complex electric field patterns.

B. CALCULATED ECC

For diversity and MIMO application, the correlation between signals received at the same side of a wireless link by the involved antenna is an important figure of merit for the whole system. The envelop correlation coefficient (ECC) is usually used to evaluate the diversity capability of multi-antenna system, in which low ECC value means higher isolation and large diversity gain. In general, the ECC value should be less than 0.5, so that good characteristic of diversity for mobile terminal applications can be achieved [22]. Because the detail formulae of ECC has already been discussed in [22]




FIGURE 12. Measured radiation patterns of 4G antennas at (a) 900 MHz, (b) 2000 MHz.

for diversity antenna, for brevity, it will not be shown in here. Fig. 11 shows the ECC characteristic computed from the measured complex E-field patterns. The ECC values for 4G and 5G antennas are less than 0.4 and 0.2, respectively, over their corresponding desired bands of interest.

Fig. 12 shows the measured two-dimensional radiation patterns of 4G antennas at 900 and 2000 MHz for Ant1 and Ant2. For the 4G antennas, as explained in [21], because of their symmetrical placement, Ant1 and Ant2 have demonstrated distinct complementary characteristics at the same frequency. These behaviors are advantageous for achieving smaller ECCs, which also explain the lower ECCs obtained over the operating bands. Fig. 13 shows the measured two-dimensional radiation patterns of Ant3–Ant6 at 3500 MHz. As expected, each 5G antenna element has exhibited similar radiation patterns in the three principal planes, in which near bi-directional patterns were observed in the XZ-plane, while both YZ- and XY-planes have demonstrated broadside patterns in the +Y (90°) direction.

C. CHANNEL CAPACITIES OF 5G AND 4G ANTENNAS

Similar to a SISO (single input single output) system, the channel capacity of a MIMO system is a function of the system bandwidth and the statistic of its equivalent SNR (signal to noise ratio), that is usually adopted to evaluate the system performance [23]–[25]. When the transmitter does not know the channel conditions, the power is equally divided




FIGURE 14. Calculated ergodic channel capacities of 5G antenna array prototype in an 8 × 8 MIMO system.




FIGURE 15. Calculated ergodic channel capacities of 4G antenna array prototype in an 2 × 2 MIMO system.




FIGURE 13. Measured radiation patterns of 5G antennas at 3.5 GHz.

to each transmit antenna element, and its ergodic channel capacity is defined as

$$C = E \left\{ \log_2 \left[\det \left(I + \frac{SNR}{n_T} HH^H \right) \right] \right\},$$

whereby E denotes expectation with respect to different channel realizations, I is an identity matrix, SNR denotes the mean SNR at the mobile terminal, n_T is the number of transmitting antennas, H is the channel matrix, and H^H denotes the Hermitian transpose of matrix [16]. In this case, the uncorrelated transmitting antennas, and the i.i.d. (independently identically distributed) channels with Rayleigh fading environment of SNR = 20 dB are considered. For 5G antenna module operated at 3400–3600 MHz band, theoretically, it could greatly improve the channel capacity compared with the case that only one antenna at the mobile-terminal side. The results of calculated ergodic MIMO capacity for 5G antenna module is presented in Fig. 14. The proposed 5G antenna array is compared with the case of eight ideal transmitting and receiving antennas, (ideal 8 × 8 MIMO system), and the case of one ideal transmitting and receiving antenna (ideal SISO system). It is shown that the proposed 5G antenna array in an 8 × 8 MIMO system has achieved capacity much larger than that of a SISO system, but lower than the ideal 8 × 8 MIMO system case by only about 6 bps/Hz in a uniform environment.

To ensure that the proposed 4G antenna array prototype is workable in a 2×2 MIMO system, its corresponding ergodic MIMO capacity is also calculated and presented in Fig. 15. Here, the proposed 4G antenna array is also compared with the case of two ideal transmitting and receiving antennas, (ideal 2×2 MIMO system). It is shown that the proposed 4G antenna array in an 2×2 MIMO system has achieved capacity of above 7.5 bps/Hz with a 20-dB SNR, but lower than the ideal 2×2 MIMO system case (11.5 bps/Hz) in a uniform environment.

IV. CONCLUSION

This work has successfully reported a multi-antenna module that composed of a 4G and 5G antenna modules, which can be applied for 4G/5G applications. The 4G antenna module can cover two wide operating bands of 824–960 MHz and 1710–2690 MHz, and the 5G antenna module with eight monopole antennas can cover the 3400–3600 MHz band. The ergodic channel capacities of 5G antenna array in a 8×8 MIMO system have been calculated to reach about 40 bps/Hz with a 20-dB SNR, which is approximately 7 times larger than that of an ideal SISO system. Typical results such as S-parameters, radiation efficiency, antenna gain, radiation pattern, and ECCs were measured, and they can meet the requirements of MIMO systems. Therefore, the proposed multi-antenna module is promising for future multi-mode smartphone applications. Lastly, as far as the authors concern, a combined 4G and 5G antenna modules has never been reported in the open-literature or anywhere else.

REFERENCES

- [1] W. Su, Q. Liu, H. He, and H. Zhang, "A new context awareness scheme for multi-mode mobile terminals in mobile Internet," in *Proc. IET 3rd Int. Conf. IET Wireless, Mobile Multimedia Netw. (ICWMNN)*, Sep. 2010, pp. 95–98.
- [2] T. Ohishi, N. Oodachi, S. Sekine, and H. Shoki, "A method to improve the correlation coefficient and the mutual coupling for diversity antenna," in *IEEE Antennas Propag. Soc. Int. Symp. Dig.*, Washington, DC, USA, Jul. 2005, pp. 507–510.
- [3] Y. Ding, Z. Du, K. Gong, and Z. Feng, "A novel dual-band printed diversity antenna for mobile terminals," *IEEE Trans. Antennas Propag.*, vol. 55, no. 7, pp. 2088–2096, Jul. 2007.
- [4] Z. Li, Z. Du, and K. Gong, "A novel wideband printed diversity antenna for mobile phone application," in *Proc. IEEE Antennas Propag. Soc. Int. Symp. (AP-S)*, San Diego, CA, USA, Jul. 2008, pp. 1–4.
- [5] X. Wang, Z. Du, and K. Gong, "A compact wideband planar diversity antenna covering UMTS and 2.4 GHz WLAN bands," *IEEE Antennas Wireless Propag. Lett.*, vol. 7, pp. 588–591, 2008.
- [6] A. Diallo, C. Luxey, P. Le Thuc, R. Staraj, and G. Kossiavas, "Study and reduction of the mutual coupling between two mobile phone PIFAs operating in the DCS1800 and UMTS bands," *IEEE Trans. Antennas Propag.*, vol. 54, no. 11, pp. 3063–3073, Nov. 2006.
- [7] A. Diallo, C. Luxey, P. Le Thuc, R. Staraj, and G. Kossiavas, "Enhanced two-antenna structures for universal mobile telecommunication systems diversity terminals," *IET Microw. Antennas Propag.*, vol. 2, no. 1, pp. 93–101, Feb. 2008.
- [8] A. Chebihi, D. Nyberg, A. Diallo, C. Luxey, P. Le Thuc, and R. Staraj, "User's head and hand influence on the diversity performance of neutralized two-antenna systems for UMTS handsets," in *Proc. IEEE Antennas Propag. Soc. Int. Symp. (AP-S)*, San Diego, CA, USA, Jul. 2008, pp. 1–4.
- [9] Y.-L. Ban, Z.-X. Chen, Z. Chen, K. Kang, and J. L.-W. Li, "Decoupled closely spaced heptaband antenna array for WWAN/LTE smartphone applications," *IEEE Antennas Wireless Propag. Lett.*, vol. 13, pp. 31–34, 2014.
- [10] A. Bleicher, "The 5G phone future," *IEEE Spectr.*, vol. 50, no. 7, pp. 15–16, Jul. 2013.
- [11] *World Radiocommunication Conference Allocates Spectrum for Future Innovation*, accessed on Nov. 27, 2015. [Online]. Available: http://www.itu.int/net/pressoffice/press_releases/2015/56.aspx#VqpBJ_197IV
- [12] K.-L. Wong, T.-W. Kang, and M.-F. Tu, "Internal mobile phone antenna array for LTE/WWAN and LTE MIMO operations," *Microw. Opt. Technol. Lett.*, vol. 53, no. 7, pp. 1569–1573, Jul. 2011.
- [13] K.-L. Wong and H.-J. Chang, "Hybrid dual-antenna for the 3.6-GHz LTE operation in the tablet computer," *Microw. Opt. Technol. Lett.*, vol. 57, pp. 2592–2598, Nov. 2015.
- [14] S. A. Nasir, M. Mustaqim, and B. A. Khawaja, "Antenna array for 5th generation 802.11ac Wi-Fi applications," in *Proc. 11th Annu. High Capacity Opt. Netw. Emerg./Enabling Technol. (Photonics for Energy)*, Charlotte, NC, USA, Dec. 2014, pp. 20–24.
- [15] K. Werner, H. Asplund, B. Halvarsson, A. K. Kathrein, N. Jalden, and D. V. P. Figueiredo, "LTE-A field measurements: 8×8 MIMO and carrier aggregation," in *Proc. IEEE 77th Veh. Technol. Conf. (VTC Spring)*, Dresden, Germany, Jun. 2013, pp. 1–5.
- [16] A. A. Al-Hadi, J. Ilvonen, R. Valkonen, and V. Viikari, "Eight-element antenna array for diversity and mimo mobile terminal in LTE 3500 MHz band," *Microw. Opt. Technol. Lett.*, vol. 56, no. 6, pp. 1323–1327, Jun. 2014.
- [17] K.-L. Wong and J. Y. Lu, "3.6-GHz 10-antenna array for mimo operation in the smartphone," *Microw. Opt. Technol. Lett.*, vol. 57, no. 7, pp. 1699–1704, Jul. 2015.
- [18] K. L. Wong, J.-Y. Lu, L.-Y. Chen, W.-Y. Li, and Y.-L. Ban, "8-antenna and 16-antenna arrays using the quad-antenna linear array as a building block for the 3.5-GHz LTE MIMO operation in the smartphone," *Microw. Opt. Technol. Lett.*, vol. 58, no. 1, pp. 174–181, Jan. 2016.
- [19] D. Wu, S. W. Cheung, and T. I. Yuk, "A compact loop antenna with seven resonant modes for smartphones," in *Proc. IEEE-APS Topical Conf. Antennas Propag. Wireless Commun. (APWC)*, Turin, Italy, Sep. 2015, pp. 355–358, doi: 10.1109/APWC.2015.7300159.
- [20] D. Wu, S. W. Cheung, and T. I. Yuk, "A compact and low-profile loop antenna with multiband operation for ultra-thin smartphones," *IEEE Trans. Antennas Propag.*, vol. 63, no. 6, pp. 2745–2750, Jun. 2015, doi: 10.1109/TAP.2015.2412962.
- [21] Y.-L. Ban, Z.-X. Chen, Z. Chen, K. Kang, and J. L.-W. Li, "Decoupled hepta-band antenna array for WWAN/LTE smartphone applications," *IEEE Antennas Wireless Propag. Lett.*, vol. 13, pp. 999–1002, 2014.
- [22] R. G. Vaughan and J. B. Andersen, "Antenna diversity in mobile communications," *IEEE Trans. Veh. Technol.*, vol. 36, no. 4, pp. 149–172, Nov. 1987.
- [23] G. J. Foschini, "Layered space-time architecture for wireless communication in a fading environment when using multi-element antennas," *Bell Labs Tech. J.*, vol. 1, no. 2, pp. 41–59, 1996.
- [24] G. J. Foschini, Jr., and M. J. Gans, "On limits of wireless communications in a fading environment when using multiple antennas," *Wireless Pers. Commun.*, vol. 6, no. 3, pp. 311–335, 1998.
- [25] L. Zheng and D. N. C. Tse, "Diversity and multiplexing: A fundamental tradeoff in multiple-antenna channels," *IEEE Trans. Inf. Theory*, vol. 49, no. 5, pp. 1073–1096, May 2003.



YONG-LING BAN was born in Henan, China. He received the B.S. degree in mathematics from Shandong University, the M.S. degree in electromagnetics from Peking University, and the Ph.D. degree in microwave engineering from the University of Electronic Science and Technology of China (UESTC), in 2000, 2003, and 2006, respectively. In 2006, he joined the Xi'an Mechanical and Electric Information Institute as a Microwave Engineer. He then joined Huawei Technologies Company, Ltd., Shenzhen, China, as an RF Antenna Design Engineer and then as a Senior Design Engineer, where he designed and implemented various terminal antennas for 15 data card and mobile phone products customized from leading telecommunication industries, such as Vodafone. Since 2010, he has been an Associate Professor of Microwave Engineering with UESTC. From 2014 to 2015, he visited the Queen Mary University of London as a Visiting Scholar. His research interests include wideband small antennas for 4G/5G handset devices, MIMO antenna, and millimeter wave antenna array. He has authored over 60 referred journal and conference papers on these topics and holds 20 granted and pending Chinese and overseas patents.



CHUAN LI was born in Sichuan, China, in 1989. He received the B.S. degree in applied physics from the Chengdu University of Technology in 2012. He is currently pursuing the master's degree in microwave engineering with the School of Electronic Engineering, University of Electronic Science and Technology of China, Chengdu. His main research interests are multiple-input multiple-output antennas for 4G/5G wireless terminal devices and multiband/wideband LTE/WWAN

small phone antennas.



CHOW-YEN-DESMOND SIM (M'07–SM'13) was born in Singapore in 1971. He received the B.Sc. degree from the Engineering Department, University of Leicester, U.K., in 1998, and the Ph.D. degree from the Radio System Group, Engineering Department, University of Leicester, in 2003. From 2003 to 2007, he was an Assistant Professor with the Department of Computer and Communication Engineering, Chienkuo Technology University, Changhua, Taiwan. In 2007,

he joined the Department of Electrical Engineering, Feng Chia University (FCU), Taichung, Taiwan, as an Associate Professor, where he became a Full Professor in 2012. He is currently serving as the Executive Officer of Master's Program with the College of Information and Electrical Engineering (Industrial Research and Development), the Director of Intelligent IoT Industrial Ph.D. Program, and the Director of the Antennas and Microwave Circuits Innovation Research Center with FCU. He has authored or co-authored over 80 SCI papers. His current research interests include antenna design, VHF/UHF tropospheric propagation, and RFID applications. He is a fellow of the Institute of Engineering and Technology, a Senior Member of the IEEE Antennas and Propagation Society, and a Life Member of the IAET. In 2015, he was invited to become the Distinguished Chair Professor (ZhiQian Professor) with the School of Communication and Information Engineering, Shanghai University (SHU). He was the TPC Member of the APMC 2012, the APCAP 2015, and the IMWS-Bio 2015. He served as the TPC Sub-Committee Chair (Antenna) of the ISAP 2014. He was a recipient of the IEEE Antennas and Propagation Society Top 10 Outstanding Reviewer Award for Year (2013/2014) and (2014/2015). He received the fee waiver Ph.D. Scholarship from the Radio System Group, Engineering Department, University of Leicester, in 1999. He was invited as the Workshop Speaker in APEMC 2015, and the Invited Speaker of TDAT 2015. He serves as the TPC Chair of the APCAP 2016, and the Chapter Chair of the IEEE AP-Society, Taipei Chapter (from 2016 to 2018).



GANG WU (M'05) received the B.S. and M.S. degree in radio communications engineering from the Chongqing University of Post and Telecommunications, Chongqing, China, in 1996 and 1999, respectively, and the Ph.D. degree in communications and information systems from the University of Electronic Science and Technology of China (UESTC), Chengdu, China, in 2004. He joined UESTC in 2004 as a Lecturer. He was a Research Fellow with the Positioning and Wireless

Technology Centre, Nanyang Technological University, Singapore, from 2005 to 2007, and a Visiting Scholar with the Georgia Institute of Technology, Atlanta, GA, USA, from 2009 to 2010. He is an Associate Professor with the National Key Laboratory of Science and Technology on Communications, UESTC. His research interest includes MIMO-OFDM, cooperative communications, cognitive radio, resource allocation and scheduling for wireless networks, and energy-efficient wireless networks. He served as a Technical Reviewer of dozens of international journals and conferences. He has also been a Technical Program Committee Member of several international conferences. He was an Exemplary Reviewer of the IEEE COMMUNICATIONS LETTERS in 2011 and received the IEEE Globecom 2012 Best Paper Award.



KIN-LU WONG (M'91–SM'97–F'07) received the B.S. degree from National Taiwan University, Taipei, Taiwan, in 1981, and the M.S. and Ph.D. degrees from Texas Tech University, Lubbock, TX, USA, in 1984 and 1986, respectively, all in electrical engineering. From 1986 to 1987, he was a Visiting Scientist with the Max-Planck-Institute for Plasma Physics, Munich, Germany. Since 1987, he has been with the Electrical Engineering Department, National Sun Yat-sen

University (NSYSU), Kaohsiung, Taiwan, where he became a Professor in 1991. From 1998 to 1999, he was a Visiting Scholar with the ElectroScience Laboratory, Ohio State University, Columbus, OH, USA. In 2005, he was elected as the Sun Yat-sen Chair Professor with NSYSU. He also served as a Chairman of the Electrical Engineering Department from 1994 to 1997, the Vice President for Research Affairs from 2005 to 2008, and the Senior Vice President of NSYSU from 2007 to 2012. He has authored over 550 refereed journal papers and 280 conference articles and has personally supervised 53 graduated Ph.D. students. He holds over 200 patents, including U.S., Taiwan, China, and EU patents. His published articles have been cited over 21 000 times with an H-index of 69 in Google Scholar. He has also authored the books entitled *Design of Nonplanar Microstrip Antennas and Transmission Lines* (Wiley, 1999), *Compact and Broadband Microstrip Antennas* (Wiley, 2002), and *Planar Antennas for Wireless Communications* (Wiley, 2003). He was elected as a Thomson Reuters Highly Cited Researcher in 2014 and 2015. In 2008, the research achievements on handheld device antennas of the NSYSU's Antenna Laboratory led by him was selected to be the top 50 scientific achievements of Taiwan Ministry of Science and Technology, Taipei, in past 50 years (from 1959 to 2009). He is an Elected IEEE AP-S AdCom Member. He served or currently serves as the IEEE AP-S Paper Awards Committee Member, the IEEE AP-S Field Awards Committee Member, an Associate Editor of the IEEE Transactions on Antennas and Propagation, and an AdCom Member of the IEEE Tainan Section. He is also a PE7 Panel Member of the 2015 European Research Council Advanced Grant Panel and a Chief Consultant of the Institute of Antenna Engineers of Taiwan, Taipei. He also served as the Chair of the judge panel for the 2014 and 2015 National Terminal Antenna Design Competition organized by the Taiwan Ministry of Economics. He served as the General Chair of 2012 APMC and 2014 ISAP, Kaohsiung, Taiwan, and will also be the General Chair of 2016 APCAP, Kaohsiung. He has been an International Steering Committee Member for many international conferences. He was a recipient of the 2010 Outstanding Research Award of the Pan Wen Yuan Foundation and selected as the Top 100 Honor of Taiwan by Global Views Monthly in 2010 for his contribution in mobile antenna researches. In 2012, he was also a recipient of the Academic Award from the Taiwan Ministry of Education, the Outstanding Distinguished Researcher Award from the Taiwan Ministry of Science and Technology in 2013, the Outstanding Research Award three times from the Taiwan National Science Council, Taipei in 1995, 2000, and 2002, the Outstanding Electrical Engineering Professor Award from the Institute of Electrical Engineers of Taiwan in 2003, and the Outstanding Engineering Professor Award from the Institute of Engineers of Taiwan in 2004. He and his graduate students were a recipient of the best paper award (APMC Prize) in 2008 APMC, and the Best Student Paper Award/Young Scientist Award in 2007 ISAP, 2008 APMC, 2009 ISAP, 2010 ISAP, and 2012 ISAP. His graduate students also received the first prize of the 2007 and 2009 Taiwan National Mobile Handset Antenna Design Competition.

• • •